



Tag

Contactless key fob to control security modes

Sold in packages of 3, 10, or 100 devices




Convenient access to a system

- One Tag key fob can be paired with 13 Ajax systems.
- Set the name and access permissions for each key fob in the app.
- Modify Tag access permissions in real time: revoke, restrict, change, or expand users' access to security systems and groups.
- Every action is recorded in the event log, providing a history of system interactions.

Sabotage resistance

- Copy protection.
- Triple DES encryption and AES hardware encryption with a 128-bit key.
- Authorization confirmation. The feature allows setting up two-factor authentication to control the system security modes, which requires both Tag and a passcode for authorization.



Connection and configuration

- Tag is added to the system through the app by presenting the key fob to the keypad in the settings menu.
- Access settings can be changed remotely.

Pass. Same device,
but in a different form.

Contactless card to control security modes.






Superior, Fibra, and Baseline product lines are mutually compatible. This opens up numerous possibilities for building systems of any configuration.

<p>Compatibility</p> <p>KeyPad Plus Jeweller KeyPad TouchScreen Jeweller KeyPad TouchScreen Fibra KeyPad S Plus Jeweller</p>	<p>Contactless authentication</p> <p>Communication technology DESFire®</p> <p>Operating standard ISO 14443-A (13.56 MHz)</p> <p>Encryption Triple DES encryption AES hardware encryption with a 128-bit key</p>	<p>Key features</p> <p>Assigned users Name and access permissions for each key fob in an Ajax app</p> <p>Ajax hubs up to 13 in memory</p>	<p>Sabotage protection</p> <p>Authentication Protection from signal interception</p>
<p>Enclosure</p> <p>Color Black White</p> <p>Dimensions 45 × 32 × 0.6 mm 1,77" × 1.26" × 0.03"</p> <p>Weight 7 g 0,2 oz</p> <p>Operating temperature range from -10 °C to +40 °C from 14 °F to 104 °F</p> <p>Operating humidity up to 75%</p>	<p>Complete set</p> <p>3, 10, or 100 devices (depending on the kit) Quick start guide</p>		



For detailed information, scan the QR code or follow the link:
ajax.systems/support/devices/access-devices/

-  support@ajax.systems
-  [@AjaxSystemsSupport_Bot](https://twitter.com/AjaxSystemsSupport_Bot)
-  [ajax.systems](https://www.ajax.systems)